

3VJ Internal Accessories

Frame Size	Reference Image	Accessory compartment/coil voltage	3VJ10 (VJ1 125X)	3VJ11 (VJ1 125)	3VJ12 (VJ1 250)	3VJ13 (VJ1 400)	3VJ14 (VJ1 630)
Accessory							
Auxiliary Switches		Left	3VJ9018-0AN11	3VJ9218-0AN11		3VJ9417-0AN11	
		Right	-	3VJ9218-0AN21		3VJ9417-0AN21	
Alarm Switches		Left	3VJ9018-0AA11	3VJ9118-0AA11	3VJ9218-0AA11	3VJ9417-0AA11	
		Right	-	3VJ9118-0AA21	3VJ9218-0AA21	3VJ9417-0AA21	
Auxiliary + Alarm Switches		Left	3VJ9018-0AD11	3VJ9118-0AD11	3VJ9218-0AD11	3VJ9417-0AD11	
		Right	-	3VJ9118-0AD21	3VJ9218-0AD21	3VJ9417-0AD21	
Shunt Trip (Right)		24V DC	*	3VJ9218-0ST11		-	
		24V AC/DC	-	-		3VJ9417-0ST21	
		48V DC	*	3VJ9218-0ST12		-	
		48V AC/DC	-	-		3VJ9417-0ST22	
		110V DC	3VJ9018-0ST15	3VJ9218-0ST15		-	
		110V AC/DC	-	-		3VJ9417-0ST25	
		110V AC	3VJ9018-0ST35	3VJ9218-0ST35		-	
		220V AC	3VJ9018-0ST36	3VJ9218-0ST36		3VJ9417-0ST36	
		415V AC	3VJ9018-0ST37	3VJ9218-0ST37		3VJ9417-0ST37	
Under-voltage Release (Left)		24V DC	-	3VJ9218-0UV11		-	
		48V DC		3VJ9218-0UV12		-	
		220V AC		3VJ9218-0UV36		3VJ9417-0UV36	
		415V AC		3VJ9218-0UV37		3VJ9417-0UV37	

Notes:

Internal accessories are available only for 2P, 3P & 4P MCCBs

3VJ9218-OST..shunt releases can be used with 3VJ11(Frame VJ1 125) & 3VJ12(Frame VJ1 250) only

- : NA

* : Coming soon