

AX260 ... AX370 3-pole contactors

132 to 200 kW

AC operated



AX260 ... AX370

Description

AX260 ... AX370 contactors are mainly used for controlling 3-phase motors and power circuits up to 690 V AC.

These contactors are of the block type design with:

- 3 main poles and side mounted auxiliary contact block
- control circuit: AC operated
- add-on auxiliary contact blocks for side mounting and a wide range of accessories.

2

Ordering details

IEC		Rated control circuit voltage		Auxiliary contacts fitted		Type	Order code	Weight Pkg (1 pce) kg
Rated power 400 V AC-3 kW	operational current $\theta \leq 40^\circ\text{C}$ AC-1 A	Uc (1) V 50 Hz	V 60 Hz	1	1			
132	400	24	24	1	1	AX260-30-11-81	1SFL547074R8111	5.4
		110	110...120	1	1	AX260-30-11-84	1SFL547074R8411	5.4
		220...230	230...240	1	1	AX260-30-11-80	1SFL547074R8011	5.4
		230...240	240...260	1	1	AX260-30-11-88	1SFL547074R8811	5.4
		400...415	415...440	1	1	AX260-30-11-86	1SFL547074R8611	5.4
160	500	24	24	1	1	AX300-30-11-81	1SFL587074R8111	5.4
		110	110...120	1	1	AX300-30-11-84	1SFL587074R8411	5.4
		220...230	230...240	1	1	AX300-30-11-80	1SFL587074R8011	5.4
		230...240	240...260	1	1	AX300-30-11-88	1SFL587074R8811	5.4
		400...415	415...440	1	1	AX300-30-11-86	1SFL587074R8611	5.4
200	600	24	24	1	1	AX370-30-11-81	1SFL607074R8111	5.4
		110	110...120	1	1	AX370-30-11-84	1SFL607074R8411	5.4
		220...230	230...240	1	1	AX370-30-11-80	1SFL607074R8011	5.4
		230...240	240...260	1	1	AX370-30-11-88	1SFL607074R8811	5.4
		400...415	415...440	1	1	AX370-30-11-86	1SFL607074R8611	5.4

(1) for other voltage version see page no. 2/51