

AX95 ... AX150 3-pole contactors

45 to 75 kW

AC operated



AX95 ... AX150

Description

AX95 ... AX150 contactors are mainly used for controlling 3-phase motors and power circuits up to 690 V AC.

These contactors are of the block type design with:

- 3 main poles and side mounted auxiliary contact block
- control circuit: AC operated
- add-on auxiliary contact blocks for front or side mounting and a wide range of accessories.

2

Ordering details

IEC Rated operational power 400 V AC-3 kW	Rated operational current $\theta \leq 40^\circ\text{C}$ AC-1 A	Rated control circuit voltage Uc (1)		Auxiliary contacts fitted Y Y	Type	Order code	Weight
		V 50 Hz	V 60 Hz				Pkg (1 pce)
							kg
45	145	24	24	1 1	AX95-30-11-81	1SFL431074R8111	2.08
		110	110...120	1 1	AX95-30-11-84	1SFL431074R8411	2.08
		220...230	230...240	1 1	AX95-30-11-80	1SFL431074R8011	2.08
		230...240	240...260	1 1	AX95-30-11-88	1SFL431074R8811	2.08
		400...415	415...440	1 1	AX95-30-11-86	1SFL431074R8611	2.08
55	160	24	24	1 1	AX115-30-11-81	1SFL981074R8111	2.08
		110	110...120	1 1	AX115-30-11-84	1SFL981074R8411	2.08
		220...230	230...240	1 1	AX115-30-11-80	1SFL981074R8011	2.08
		230...240	240...260	1 1	AX115-30-11-88	1SFL981074R8811	2.08
		400...415	415...440	1 1	AX115-30-11-86	1SFL981074R8611	2.08
75	190	24	24	1 1	AX150-30-11-81	1SFL991074R8111	2.08
		110	110...120	1 1	AX150-30-11-84	1SFL991074R8411	2.08
		220...230	230...240	1 1	AX150-30-11-80	1SFL991074R8011	2.08
		230...240	240...260	1 1	AX150-30-11-88	1SFL991074R8811	2.08
		400...415	415...440	1 1	AX150-30-11-86	1SFL991074R8611	2.08

(1) for other voltage version see page no. 2/51