

Siemens  
EcoTech



SIMATIC S7-1500 Analog input/output module AI 4x U/I/R/RTD/TC ST; 4 channels in groups of 4; Hardware interrupts; Diagnostics AQ 2x U/I ST; 2 channels in groups of 2; Substitute value; Diagnostics Common mode voltage approx. 10 V 16 bit; Accuracy 0.3%; Delivery including push-in front connector, infeed element, shield bracket and shield terminal



| General information   |  |
|---|--|
| Product type designation  | AI 4xU/I/RTD/TC /AQ 2xU/I ST                               |
| HW functional status  | from FS01  |
| Firmware version  | V1.0.0   |
| <ul style="list-style-type: none"> <li>FW update possible</li> </ul>  | Yes  |
| Product function  |  |
| <ul style="list-style-type: none"> <li>I&amp;M data</li> <li>Isochronous mode</li> <li>Prioritized startup</li> <li>Measuring range scalable</li> <li>Scalable measured values</li> <li>Adjustment of measuring range</li> <li>Output range scalable</li> </ul> | Yes; I&M0 to I&M3<br>No<br>No<br>No<br>No<br>No<br>No      |
| Engineering with  |  |
| <ul style="list-style-type: none"> <li>STEP 7 TIA Portal configurable/integrated from version</li> <li>STEP 7 configurable/integrated from version</li> <li>PROFIBUS from GSD version/GSD revision</li> <li>PROFINET from GSD version/GSD revision</li> </ul>   | V13 / V13.0.2<br>V5.5 SP3 / -<br>V1.0 / V5.1<br>V2.3 / -   |
| Operating mode  |  |
| <ul style="list-style-type: none"> <li>Oversampling</li> <li>MSI</li> <li>MSO</li> </ul>  | No<br>Yes<br>Yes   |
| CiR - Configuration in RUN  |  |
| Reparameterization possible in RUN  | Yes  |
| Calibration possible in RUN   | Yes  |
| Supply voltage  |  |
| Rated value (DC)  | 24 V   |
| permissible range, lower limit (DC)   | 19.2 V   |
| permissible range, upper limit (DC)   | 28.8 V   |
| Reverse polarity protection   | Yes  |
| Input current   |  |
| Current consumption, max.   | 200 mA   |
| Encoder supply  |  |
| 24 V encoder supply   |  |
| <ul style="list-style-type: none"> <li>Short-circuit protection</li> <li>Output current, max.</li> </ul>  | Yes<br>20 mA; Max. 47 mA per channel for a duration < 10 s |
| Power   |  |

|   |   |
|---|---|
| Power available from the backplane bus                                | 0.7 W   |
| <b>Power loss</b>   |   |
| Power loss, typ.  | 3.3 W   |
| <b>Analog inputs</b>  |   |
| Number of analog inputs   | 4   |
| • For current measurement   | 4   |
| • For voltage measurement   | 4   |
| • For resistance/resistance thermometer measurement                   | 2   |
| • For thermocouple measurement  | 4   |
| permissible input voltage for voltage input (destruction limit), max. | 28.8 V  |
| permissible input current for current input (destruction limit), max. | 40 mA   |
| Constant measurement current for resistance-type transmitter, typ.    | 150 Ohm, 300 Ohm, 600 Ohm, Pt100, Pt200, Ni100: 1.25 mA; 6 000 Ohm, Pt500, Pt1000, Ni1000, LG-Ni1000: 0.625 mA; PTC: 0.472 mA |
| Technical unit for temperature measurement adjustable                 | Yes; °C/°F/K  |
| Analog input with oversampling  | No  |
| Standardization of measured values                                    | No  |
| <b>Input ranges (rated values), voltages</b>                          |   |
| • 0 to +5 V   | No  |
| • 0 to +10 V  | No  |
| • 1 V to 5 V  | Yes   |
| — Input resistance (1 V to 5 V)                                       | 100 kΩ  |
| • -1 V to +1 V  | Yes   |
| — Input resistance (-1 V to +1 V)                                     | 10 MΩ   |
| • -10 V to +10 V  | Yes   |
| — Input resistance (-10 V to +10 V)                                   | 100 kΩ  |
| • -2.5 V to +2.5 V  | Yes   |
| — Input resistance (-2.5 V to +2.5 V)                                 | 10 MΩ   |
| • -25 mV to +25 mV  | No  |
| • -250 mV to +250 mV  | Yes   |
| — Input resistance (-250 mV to +250 mV)                               | 10 MΩ   |
| • -5 V to +5 V  | Yes   |
| — Input resistance (-5 V to +5 V)                                     | 100 kΩ  |
| • -50 mV to +50 mV  | Yes   |
| — Input resistance (-50 mV to +50 mV)                                 | 10 MΩ   |
| • -500 mV to +500 mV  | Yes   |
| — Input resistance (-500 mV to +500 mV)                               | 10 MΩ   |
| • -80 mV to +80 mV  | Yes   |
| — Input resistance (-80 mV to +80 mV)                                 | 10 MΩ   |
| <b>Input ranges (rated values), currents</b>                          |   |
| • 0 to 20 mA  | Yes   |
| — Input resistance (0 to 20 mA)                                       | 25 Ω; Plus approx. 42 ohms for overvoltage protection by PTC  |
| • -20 mA to +20 mA  | Yes   |
| — Input resistance (-20 mA to +20 mA)                                 | 25 Ω; Plus approx. 42 ohms for overvoltage protection by PTC  |
| • 4 mA to 20 mA   | Yes   |
| — Input resistance (4 mA to 20 mA)                                    | 25 Ω; Plus approx. 42 ohms for overvoltage protection by PTC  |
| <b>Input ranges (rated values), thermocouples</b>                     |   |
| • Type B  | Yes   |
| — Input resistance (Type B)   | 10 MΩ   |
| • Type C  | No  |
| • Type E  | Yes   |
| — Input resistance (Type E)   | 10 MΩ   |
| • Type J  | Yes   |
| — Input resistance (type J)   | 10 MΩ   |
| • Type K  | Yes   |
| — Input resistance (Type K)   | 10 MΩ   |
| • Type L  | No  |
| • Type N  | Yes   |
| — Input resistance (Type N)   | 10 MΩ   |
| • Type R  | Yes   |

|  |                       |
|--|-----------------------|
| — Input resistance (Type R)                                | 10 MΩ                 |
| • Type S   | Yes                   |
| — Input resistance (Type S)                                | 10 MΩ                 |
| • Type T   | Yes                   |
| — Input resistance (Type T)                                | 10 MΩ                 |
| • Type U   | No                    |
| • Type TXK/TXK(L) to GOST                                  | No                    |
| <b>Input ranges (rated values), resistance thermometer</b> |                       |
| • Cu 10  | No                    |
| • Cu 10 according to GOST                                  | No                    |
| • Cu 50  | No                    |
| • Cu 50 according to GOST                                  | No                    |
| • Cu 100   | No                    |
| • Cu 100 according to GOST                                 | No                    |
| • Ni 10  | No                    |
| • Ni 10 according to GOST                                  | No                    |
| • Ni 100   | Yes; Standard/climate |
| — Input resistance (Ni 100)                                | 10 MΩ                 |
| • Ni 100 according to GOST                                 | No                    |
| • Ni 1000  | Yes; Standard/climate |
| — Input resistance (Ni 1000)                               | 10 MΩ                 |
| • Ni 1000 according to GOST                                | No                    |
| • LG-Ni 1000   | Yes; Standard/climate |
| — Input resistance (LG-Ni 1000)                            | 10 MΩ                 |
| • Ni 120   | No                    |
| • Ni 120 according to GOST                                 | No                    |
| • Ni 200   | No                    |
| • Ni 200 according to GOST                                 | No                    |
| • Ni 500   | No                    |
| • Ni 500 according to GOST                                 | No                    |
| • Pt 10  | No                    |
| • Pt 10 according to GOST                                  | No                    |
| • Pt 50  | No                    |
| • Pt 50 according to GOST                                  | No                    |
| • Pt 100   | Yes; Standard/climate |
| — Input resistance (Pt 100)                                | 10 MΩ                 |
| • Pt 100 according to GOST                                 | No                    |
| • Pt 1000  | Yes; Standard/climate |
| — Input resistance (Pt 1000)                               | 10 MΩ                 |
| • Pt 1000 according to GOST                                | No                    |
| • Pt 200   | Yes; Standard/climate |
| — Input resistance (Pt 200)                                | 10 MΩ                 |
| • Pt 200 according to GOST                                 | No                    |
| • Pt 500   | Yes; Standard/climate |
| — Input resistance (Pt 500)                                | 10 MΩ                 |
| • Pt 500 according to GOST                                 | No                    |
| <b>Input ranges (rated values), resistors</b>              |                       |
| • 0 to 150 ohms  | Yes                   |
| — Input resistance (0 to 150 ohms)                         | 10 MΩ                 |
| • 0 to 300 ohms  | Yes                   |
| — Input resistance (0 to 300 ohms)                         | 10 MΩ                 |
| • 0 to 600 ohms  | Yes                   |
| — Input resistance (0 to 600 ohms)                         | 10 MΩ                 |
| • 0 to 3000 ohms   | No                    |
| • 0 to 6000 ohms   | Yes                   |
| — Input resistance (0 to 6000 ohms)                        | 10 MΩ                 |
| • PTC  | Yes                   |
| — Input resistance (PTC)                                   | 10 MΩ                 |
| <b>Thermocouple (TC)</b>                                   |                       |
| <b>Temperature compensation</b>                            |                       |
| — parameterizable  | Yes                   |

|  |   |
|--|---|
| — internal temperature compensation                                    | Yes   |
| — external temperature compensation via RTD                            | Yes   |
| — Compensation for 0 °C reference point temperature                    | Yes; fixed value can be set   |
| — Reference channel of the module                                      | No  |
| <b>Cable length</b>  |   |
| • shielded, max.   | 800 m; for U/I, 200 m for R/RTD, 50 m for TC  |
| <b>Analog outputs</b>  |   |
| Number of analog outputs   | 2   |
| Voltage output, short-circuit protection                               | Yes   |
| Voltage output, short-circuit current, max.                            | 24 mA   |
| Current output, no-load voltage, max.                                  | 22 V  |
| Cycle time (all channels), min.  | 3.2 ms; ±0.5 ms, regardless of the number of activated channels   |
| <b>Output ranges, voltage</b>  |   |
| • 0 to 10 V  | Yes   |
| • 1 V to 5 V   | Yes   |
| • -5 V to +5 V   | No  |
| • -10 V to +10 V   | Yes   |
| <b>Output ranges, current</b>  |   |
| • 0 to 20 mA   | Yes   |
| • -20 mA to +20 mA   | Yes   |
| • 4 mA to 20 mA  | Yes   |
| <b>Connection of actuators</b>   |   |
| • for voltage output two-wire connection                               | Yes   |
| • for voltage output four-wire connection                              | Yes   |
| • for current output two-wire connection                               | Yes   |
| <b>Load impedance (in rated range of output)</b>                       |   |
| • with voltage outputs, min.   | 1 kΩ; 0.5 kΩ at 1 to 5 V  |
| • with voltage outputs, capacitive load, max.                          | 1 μF  |
| • with current outputs, max.   | 750 Ω   |
| • with current outputs, inductive load, max.                           | 10 mH   |
| <b>Cable length</b>  |   |
| • shielded, max.   | 800 m; for current, 200 m for voltage   |
| <b>Analog value generation for the inputs</b>                          |   |
| <b>Integration and conversion time/resolution per channel</b>          |   |
| • Resolution with overrange (bit including sign), max.                 | 16 bit  |
| • Integration time, parameterizable                                    | Yes   |
| • Integration time (ms)  | 2,5 / 16,67 / 20 / 100 ms   |
| • Basic conversion time, including integration time (ms)               | 9 / 23 / 27 / 107 ms  |
| — additional conversion time for wire-break monitoring                 | 9 ms  |
| — additional conversion time for resistance measurement                | 150 ohm, 300 ohm, 600 ohm, Pt100, Pt200, Ni100: 2 ms, 6000 ohm, Pt500, Pt1000, Ni1000, LG-Ni1000, PTC: 4 ms |
| • Interference voltage suppression for interference frequency f1 in Hz | 400 / 60 / 50 / 10  |
| • Time for offset calibration (per module)                             | Basic conversion time of the slowest channel  |
| <b>Smoothing of measured values</b>                                    |   |
| • parameterizable  | Yes   |
| • Step: None   | Yes   |
| • Step: low  | Yes   |
| • Step: Medium   | Yes   |
| • Step: High   | Yes   |
| <b>Analog value generation for the outputs</b>                         |   |
| <b>Integration and conversion time/resolution per channel</b>          |   |
| • Resolution with overrange (bit including sign), max.                 | 16 bit  |
| • Conversion time (per channel)  | 0.5 ms  |
| <b>Settling time</b>   |   |
| • for resistive load   | 1.5 ms  |
| • for capacitive load  | 2.5 ms  |
| • for inductive load   | 2.5 ms  |
| <b>Encoder</b>   |   |
| <b>Connection of signal encoders</b>                                   |   |
| • for voltage measurement  | Yes   |

|  |  |
|--|--|
| <ul style="list-style-type: none"> <li>• for current measurement as 2-wire transducer <ul style="list-style-type: none"> <li>— Burden of 2-wire transmitter, max.</li> </ul> </li> <li>• for current measurement as 4-wire transducer</li> <li>• for resistance measurement with two-wire connection</li> <li>• for resistance measurement with three-wire connection</li> <li>• for resistance measurement with four-wire connection</li> </ul> | <p>Yes</p> <p>820 Ω</p> <p>Yes</p> <p>Yes; Only for PTC</p> <p>Yes; All measuring ranges except PTC; internal compensation of the cable resistances</p> <p>Yes; All measuring ranges except PTC</p>  |
| <b>Errors/accuracies</b>   |  |
| Linearity error (relative to input range), (+/-)   | 0.02 %   |
| Temperature error (relative to input range), (+/-)   | 0.005 %/K; With TC type T 0.02 ± % / K   |
| Crosstalk between the inputs, max.   | -80 dB   |
| Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)  | 0.02 %   |
| Output ripple (relative to output range, bandwidth 0 to 50 kHz), (+/-)   | 0.02 %   |
| Linearity error (relative to output range), (+/-)  | 0.15 %   |
| Temperature error (relative to output range), (+/-)  | 0.002 %/K  |
| Crosstalk between the outputs, max.  | -100 dB  |
| Repeat accuracy in steady state at 25 °C (relative to output range), (+/-)   | 0.05 %   |
| Temperature error of internal compensation   | ±6 °C  |
| note regarding accuracy  | at temperatures below 0 °C, the figures for operating error and temperature error are doubled  |
| <b>Operational error limit in overall temperature range</b>  |  |
| <ul style="list-style-type: none"> <li>• Voltage, relative to input range, (+/-)</li> <li>• Current, relative to input range, (+/-)</li> <li>• Resistance, relative to input range, (+/-)</li> <li>• Resistance thermometer, relative to input range, (+/-)</li> <li>• Thermocouple, relative to input range, (+/-)</li> <li>• Voltage, relative to output range, (+/-)</li> <li>• Current, relative to output range, (+/-)</li> </ul>           | <p>0.3 %</p> <p>0.3 %</p> <p>0.3 %</p> <p>0.3 %; Ptxxx standard: ±1.5 K, Ptxxx climate: ±0.5 K, Nixxx standard: ±0.5 K, Nixxx climate: ±0.3 K</p> <p>0.3 %; Type B: &gt; 600 °C ±4.6 K, type E: &gt; -200 °C ±1.5 K, type J: &gt; -210 °C ±1.9 K, type K: &gt; -200 °C ±2.4 K, type N: &gt; -200 °C ±2.9 K, type R: &gt; 0 °C ±4.7 K, type S: &gt; 0 °C ±4.6 K, type T: &gt; -200 °C ±2.4 K</p> <p>0.3 %</p> <p>0.3 %</p>  |
| <b>Basic error limit (operational limit at 25 °C)</b>  |  |
| <ul style="list-style-type: none"> <li>• Voltage, relative to input range, (+/-)</li> <li>• Current, relative to input range, (+/-)</li> <li>• Resistance, relative to input range, (+/-)</li> <li>• Resistance thermometer, relative to input range, (+/-)</li> <li>• Thermocouple, relative to input range, (+/-)</li> <li>• Voltage, relative to output range, (+/-)</li> <li>• Current, relative to output range, (+/-)</li> </ul>           | <p>0.1 %</p> <p>0.1 %</p> <p>0.1 %</p> <p>0.1 %; Ptxxx standard: ±0.7 K, Ptxxx climate: ±0.2 K, Nixxx standard: ±0.3 K, Nixxx climate: ±0.15 K</p> <p>0.1 %; Type B: &gt; 600 °C ±1.7 K, type E: &gt; -200 °C ±0.7 K, type J: &gt; -210 °C ±0.8 K, type K: &gt; -200 °C ±1.2 K, type N: &gt; -200 °C ±1.2 K, type R: &gt; 0 °C ±1.9 K, type S: &gt; 0 °C ±1.9 K, type T: &gt; -200 °C ±0.8 K</p> <p>0.2 %</p> <p>0.2 %</p> |
| <b>Interference voltage suppression for <math>f = n \times (f_1 \pm 1 \%)</math>, <math>f_1</math> = interference frequency</b>  |  |
| <ul style="list-style-type: none"> <li>• Series mode interference (peak value of interference &lt; rated value of input range), min.</li> <li>• Common mode voltage, max.</li> <li>• Common mode interference, min.</li> </ul>   | <p>40 dB</p> <p>10 V</p> <p>60 dB</p>  |
| <b>Interrupts/diagnostics/status information</b>   |  |
| Diagnostics function   | Yes  |
| Substitute values connectable  | Yes  |
| <b>Alarms</b>  |  |
| <ul style="list-style-type: none"> <li>• Diagnostic alarm</li> <li>• Limit value alarm</li> </ul>  | <p>Yes</p> <p>Yes; two upper and two lower limit values in each case</p>   |
| <b>Diagnoses</b>   |  |
| <ul style="list-style-type: none"> <li>• Monitoring the supply voltage</li> <li>• Wire-break</li> <li>• Short-circuit</li> <li>• Overflow/underflow</li> </ul>   | <p>Yes</p> <p>Yes; only for input type 1 ... 5 V, 4 ... 20 mA, TC, R, RTD and output type current</p> <p>Yes; Only for output type "voltage"</p> <p>Yes</p>  |
| <b>Diagnostics indication LED</b>  |  |
| <ul style="list-style-type: none"> <li>• RUN LED</li> </ul>  | Yes; green LED   |

|  |  |
|--|--|
| • ERROR LED  | Yes; red LED   |
| • Monitoring of the supply voltage (PWR-LED)                   | Yes; green LED   |
| • Channel status display                                       | Yes; green LED   |
| • for channel diagnostics                                      | Yes; red LED   |
| • for module diagnostics                                       | Yes; red LED   |
| <b>Potential separation</b>                                    |  |
| Potential separation analog inputs                             |  |
| • between the channels   | No   |
| • between the channels, in groups of                           | 4  |
| • between the channels and backplane bus                       | Yes  |
| • Between the channels and load voltage L+                     | Yes  |
| Potential separation analog outputs                            |  |
| • between the channels   | No   |
| • between the channels, in groups of                           | 2  |
| • between the channels and backplane bus                       | Yes  |
| • Between the channels and load voltage L+                     | Yes  |
| <b>Permissible potential difference</b>                        |  |
| between the inputs (UCM)                                       | 20 V DC  |
| Between the inputs and MANA (UCM)                              | 10 V DC  |
| between S- and MANA (UCM)                                      | 8 V DC   |
| <b>Isolation</b>   |  |
| Isolation tested with  | 707 V DC (type test)   |
| <b>Standards, approvals, certificates</b>                      |  |
| Siemens Eco Profile (SEP)                                      | Siemens EcoTech  |
| Ecological footprint   |  |
| • environmental product declaration                            | Yes  |
| Global warming potential                                       |  |
| — global warming potential, (total) [CO2 eq]                   | 38.6 kg  |
| — global warming potential, (during production) [CO2 eq]       | 14.4 kg  |
| — global warming potential, (during operation) [CO2 eq]        | 24.6 kg  |
| — global warming potential, (after end of life cycle) [CO2 eq] | -0.44 kg   |
| <b>product functions / security / header</b>                   |  |
| signed firmware update   | No   |
| data integrity   | No   |
| <b>Ambient conditions</b>                                      |  |
| Ambient temperature during operation                           |  |
| • horizontal installation, min.                                | -25 °C; from FS04  |
| • horizontal installation, max.                                | 60 °C  |
| • vertical installation, min.                                  | -25 °C; from FS04  |
| • vertical installation, max.                                  | 40 °C  |
| Altitude during operation relating to sea level                |  |
| • Installation altitude above sea level, max.                  | 5 000 m; Restrictions for installation altitudes > 2 000 m, see manual   |
| <b>Dimensions</b>  |  |
| Width  | 25 mm  |
| Height   | 147 mm   |
| Depth  | 129 mm   |
| <b>Weights</b>   |  |
| Weight, approx.  | 250 g  |
| <b>Other</b>   |  |
| Note:  | Supplied incl. 40-pole push-in front connectors. Additional basic error and noise for integration time = 2.5 ms: Voltage: ±250 mV (±0.02%), ±80 mV (±0.05%), ±50 mV (±0.05%); resistance: 150 Ohms (±0.02%); resistance thermometer: Pt100 climate: ±0.08 K, Ni100 climate: ±0.08 K; thermoelement: Type B, R, S: ±3 K, type E, J, K, N, T: ±1 K |

last modified:

12/8/2024 