

AX32, AX40 3-pole contactors

15 to 18.5 kW

AC operated

2



AX32, AX40

Description

AX32, AX40 contactors are mainly used for controlling 3-phase motors and power circuits up to 690 V AC.

These contactors are of the block type design with:

- 3 main poles and 1 built-in auxiliary contact
- control circuit: AC operated
- add-on auxiliary contact blocks for front or side mounting and a wide range of accessories.

Ordering details

IEC		Rated control circuit voltage Uc (1)		Auxiliary contacts fitted		Type	Order code	Weight
Rated operational power	Rated operational current							Pkg (1 pce)
400 V	θ ≤ 40 °C							kg
AC-3	AC-1	V 50 Hz	V 60 Hz	Y	N			
kW	A							
15	55	24	24	1	0	AX32-30-10-81	1SBL281074R8110	0.71
				0	1	AX32-30-01-81	1SBL281074R8101	0.71
		110	110...120	1	0	AX32-30-10-84	1SBL281074R8410	0.71
				0	1	AX32-30-01-84	1SBL281074R8401	0.71
		220...230	230...240	1	0	AX32-30-10-80	1SBL281074R8010	0.71
				0	1	AX32-30-01-80	1SBL281074R8001	0.71
		230...240	240...260	1	0	AX32-30-10-88	1SBL281074R8810	0.71
				0	1	AX32-30-01-88	1SBL281074R8801	0.71
		400...415	415...440	1	0	AX32-30-10-86	1SBL281074R8610	0.71
				0	1	AX32-30-01-86	1SBL281074R8601	0.71
		24	24	1	0	AX40-30-10-81	1SBL321074R8110	0.71
				0	1	AX40-30-01-81	1SBL321074R8101	0.71
18.5	60	110	110...120	1	0	AX40-30-10-84	1SBL321074R8410	0.71
				0	1	AX40-30-01-84	1SBL321074R8401	0.71
		220...230	230...240	1	0	AX40-30-10-80	1SBL321074R8010	0.71
				0	1	AX40-30-01-80	1SBL321074R8001	0.71
		230...240	240...260	1	0	AX40-30-10-88	1SBL321074R8810	0.71
				0	1	AX40-30-01-88	1SBL321074R8801	0.71
		400...415	415...440	1	0	AX40-30-10-86	1SBL321074R8610	0.71
				0	1	AX40-30-01-86	1SBL321074R8601	0.71

(1) for other voltage version see page no. 2/51