Autonics

This is only for reference, the actual product does not support all combinations. For selecting the specified model, follow the Autonics website.

BTF 0 0 Т D Sensing distance Number: Sensing distance (unit: mm) Number+M: Sensing distance (unit: m)

-

Ordering Information

O Sensing type

T: Through-beam D: Diffuse reflective B: BGS reflective

 Operation mode L: Light ON D: Dark ON

-

8

Control output

No mark: NPN open collector output P: PNP open collector output

4

Product Components

Sensing type	Through-beam	Diffuse reflective	BGS reflective
Product components	Product, instruction manual		
Bracket	× 2	× 1	× 1
M2 bolt	× 4	× 2	× 2

Specifications

Model	BTF1M-TDT	BTF30-DDT	BTF15-BDT		
Sensing type	Through-beam	Diffuse reflective	BGS reflective		
Sensing distance	1 m	5 to 30 mm ⁰¹⁾	1 to 15 mm ⁰¹⁾		
Sensing target	Opaque materials	Opaque materials, translucent materials	Opaque materials, translucent materials		
Min. sensing target	≥Ø2mm	\geq Ø 0.2 mm $^{\circ 2)}$	\geq Ø 0.2 mm non- illuminated objects ⁰²⁾		
Hysteresis	-	\leq 20% of sensing distance	≤ 5% of sensing distance		
Black/white difference	-	-	$\leq 15\%$ of sensing distance		
Response time	≤1ms				
Light source	Red				
Peak emission wavelength	650 nm				
Operation mode	Light ON mode / Dark ON mode model				
Indicator	Operation indicator (red), stability indicator (green)				
Approval	C€ERE	C € ERE	C€ERE		
Unit weight (packaged)	≈ 40 g (≈ 70 g)	≈ 25 g (≈ 40 g)	≈ 25 g (≈ 40 g)		

01) Non-glossy white paper 50 × 50 mm 02) Sensing distance 10 mm

-			
Power supply	$12-24 \text{ VDC} = \pm 10 \% \text{ (ripple P-P: } \le 10\%)$		
Current consumption	It depends on the sensing type		
Through-beam	Emitter: ≤ 20 mA, receiver: ≤ 20 mA		
Reflective	\leq 20 mA		
Control output	NPN open collector output / PNP open collector output model		
Load voltage	≤ 26.4 VDC==		
Load current	≤ 50 mA		
Residual voltage	NPN: ≤ 1 VDC=, PNP: ≤ 2 VDC=		
Protection circuit	Reverse power protection circuit, output short overcurrent protection circuit		
Insulation resistance	\geq 20 M Ω (500 VDC== megger)		
Noise immunity	± 240 VDC== the square wave noise (pulse width: 1 μ s) by the noise simulator		
Dielectric strength	1,000 VAC~ 50/60 Hz for 1 min		
Vibration	1.5 mm double amplitude at frequency of 10 to 55 Hz (for 1 min) in each X, Y, Z direction for 2 hours		
Shock	500 m/s ² (\approx 50 G) in each X, Y, Z direction for 3 times		
Ambient illuminance (receiver)	e Sunlight: ≤ 10,000 k, incandescent lamp: ≤ 3,000 k		
Ambient temperature	ature -25 to 55 °C, storage: -40 to 70 °C (no freezing or condensation)		
Ambient humidity	35 to 85 %RH, storage: 35 to 85 %RH (no freezing or condensation)		
Protection rating	IP67 (IEC standard)		
Connection	Cable type		
Cable spec.	Ø 2.5 mm, 3-wire (emitter: 2-wire), 2 m		
Wire spec.	AWG 28 (0.08 mm, 19-core), insulator outer diameter: Ø 0.9 mm		
Material	Case: PBT, sensing part: PMMA, bracket: SUS304, bolt: carbon steel, sleeve: SUS304		

L 3.7 mm Flat Photoelectric Sensors



BTF Series CATALOG


For your safety, read and follow the considerations written in the instruction manual, other manuals and Autonics website.

The specifications, dimensions, etc. are subject to change without notice for product improvement. Some models may be discontinued without notice.

Features

- Ultra-thin size of only 3.7mm
- W 13 \times H 19 \times L 3.7 mm (Through-beam type)
- W 13 \times H 24 \times L 3.7 mm (Diffuse reflective type, BGS reflective type)
- Detection methods and minimum target size
- Through-beam type (BTF1M): Ø 2 mm
- Diffuse reflective type (BTF30): Ø 0.2 mm (sensing distance: 10 mm)
- BGS reflective type (BTF15): Ø 0.2 mm (sensing distance: 10 mm)
- · BGS (background suppression) minimizes detection errors from background objects and the color or material of target objects.
- Maximum sensing distance: 1 m (Through-beam type)
- Operation indicator (red) and stability indicator (green) show operation status
- Stainless steel (SUS304) mounting brackets
- IP67 protection rating (IEC standard)

Dimensions



Α	Optical axis of emitter	С	Operation indicator (red)
В	Optical axis of receiver	D	Stability indicator (green)

Bracket



